


Waveguide WR28 to 2.92 mm Adapter

Features

- Waveguide to Coaxial Adapter
- 32 GHz to 36 GHz Frequency Range
- WR28 Waveguide Interface with UG-599/U Square Cover Flange
- 2.92mm Female Coaxial Interface
- Temperature: $-10 \div 85^{\circ}\text{C}$
- Material: Aluminum Alloy



Electrical specifications

Description	Minimum	Typical	Maximum	Unit
Frequency range	32		36	GHz
VSWR			1.25 : 1	
Impedance		50		Ohm

Mechanical drawing

