

WR28 ADAPTER

Features

- Frequency: 34GHz to 35GHz
- VSWR: 1.5:1 Max
- Waveguide size: WR28
- Coax connector: 2.92mm Female
- Type: Straight 2 hole
- Temperature: -10÷85°C
- Material: Aluminum Alloy

Electrical specifications

Description	Minimum	Typical	Maximum	Unit
Frequency band	34		35	GHz
VSWR			1.5	
Insertion Loss			0.5	dB

Mechanical drawing

